



Certification Record

CUSTOMER	CLASS	FILE
c3controls Control Concepts Corporation 664 State St, Beaver PA 15009 USA	3211-05 INDUSTRIAL CONTROL EQUIPMENT-Motor Controllers - Manual	047446_0_000
Refer to Class Description for program details		

- Manual Motor Controller, suitable for use as a Disconnect Switch, Cat DDS-30, PDS-30 with suffixes, open- type, rated 30A, 600V ac; single or three phase, general purpose, panel or door mount.
- Manual Motor Controller, suitable for use as a Disconnect switch, Cat DDS-40, PDS40 with suffixes, open-type, rated 40A, 600V ac; single or three phase, general purpose, panel or door mount.
- Manual Motor Controller, suitable for use as a Disconnect Switch, Cat DDS-60, PDS-60 with suffixes, open- type, rated 60A, 600V ac; single or three phase, general purpose, panel or door mount.

Horsepower Ratings

Voltage, Vac	Single Phase(30A,40A,60A)	Three Phase(40A,60A)	Three Phase(30A)
120	2	3	3
240	5	10	5
480	10	20	10
600	10	20	10

- Power Pole Adder, Cat DPA30, PDPA30, with suffixes, open-type, rated 30A, 600V ac, single or three phase, general purpose.
- Power Pole Adder, Cat DPA40 , PDPA40, with suffixes, open-type, rated 40A, 600V ac, single or three phase, general purpose.
- Power Pole Adder, Cat DPA60, PDPA60, with suffixes, open-type, rated 60A, 600V ac, single or three phase, general purpose.
- Auxiliary Pole Adder, Cat DA01, DA10, DA11, PDA01, PDA10, PDA11 with suffixes, open-type, rated A600, 600V ac max.
- Handle Mechanism, Cat DHM, PHM, PHM2, DHM2 with suffixes, open-type.
- Short circuit rating - 10,000 rms symmetrical amperes, 600V ac.

/ey