



Certification Record

CUSTOMER	CLASS	FILE
c3controls Control Concepts Corporation	3211-05	232541
664 State St, Beaver PA 15009 USA	INDUSTRIAL CONTROL EQUIPMENT-Motor Controllers - Manual	
Refer to Class Description for program details		

- Load Break Switches also suitable for use as a motor Disconnect Switch, open type single or three phase, general purpose, panel or door mount, terminals suitable for factory and field wiring; rated as follows:

Cat No	Amp Rating	Single Phase		Horsepower rating			
		120 V	240 V	120 V	240 V	480 V	600 V
DS2-16, DDS2-16, PDS2-16	16	0.5	1.5	1.5	3	7.5	10
DS2-20, DDS2-20, PDS2-20	20	0.5	1.5	1.5	3	7.5	10
DS2-25, DDS2-25, PDS2-25	25	1.5	2	3	7.5	15	20
DS2-30, DDS2-30, PDS2-30	32	2	3	3	7.5	20	25
DS2-40, DDS2-40, PDS2-40	40	3	4	5	10	20	30
DS2-60, DDS2-60, PDS2-60	63	3	7.5	7.5	15	25	30
DS2-80, DDS2-80, PDS2-80	80	3	7.5	5	10	30	40
DS2-100, DDS2-100, PDS2-100	100	3	7.5	7.5	15	30	40
DS2-125, DDS2-125,	125	3	10	7.5	15	40	50

PDS2-125

Note: Suitable for use on a circuit capable of delivering not more than 10,000 RMS symmetrical amperes, 600 V maximum, when protected by a 90 A fuse (125 A, 100 A, 80 A devices), 70 A fuse (63 A, 40 A devices), 45 A fuse (32 A, 25 A devices), 20 A fuse (20 A, 16 A devices).

Copyright © 2009 CSA International. All rights reserved.